

Keysight Technologies

Resistance; DC Current; AC Current; and Frequency and Period Measurement Errors in Digital Multimeters

Application Note





Introduction

When you make measurements with digital multimeter (DMM), common errors will occur. The following discussion will help you eliminate potential measurement errors and achieve the greatest accuracy with a DMM. This paper covers resistance; DC current; AC current; and frequency and period measurement errors.

For a discussion of system cabling errors and DC voltage measurement errors, see application note part number 5988-5511EN. For an overview of AC voltage measurement errors, see application note part number 5988-5513EN.

Note:

The Keysight 34461A, a 6½ -digit, high-performance DMM with both benchtop and system features, will be used as an example throughout this application note.

Resistance Measurement Errors

The Keysight 34461A offers two methods for measuring resistance: 2-wire and 4-wire Ω . For both methods, the test current flows from the input HI terminal and then through the resistor being measured. For 2-wire Ω , the voltage drop across the resistor being measured is sensed internal to the multimeter. Therefore, test lead resistance is also measured. For 4-wire Ω , separate “sense” connections are required. Since no current flows in the sense leads, the resistance in these leads does not give a measurement error.

Errors for DC voltage measurements (see application note part number 5988-5511EN) also apply to resistance measurements. However, there are additional error sources that are unique to resistance measurements.

Power dissipation effects

When measuring resistors designed for temperature measurements (or other resistive devices with large temperature coefficients), be aware that the multimeter will dissipate some power in the DUT. If power dissipation is a problem, select the multimeter’s next higher measurement range to reduce the errors to acceptable levels. Table 1 shows several examples.

Table 1. Examples

Range	Test Current	DUT power at full scale
100 Ω	1 mA	100 μ W
1 k Ω	1 mA	1 mW
10 k Ω	100 μ A	100 μ W
100 k Ω	10 μ A	10 μ W
1 M Ω	5 μ A	25 μ W
10 M Ω	500 nA	2.5 μ W

Settling time effects

The Keysight 34461A has the ability to insert automatic measurement settling delays. These delays are adequate for resistance measurements with less than 200 pF of combined cable and device capacitance, which is particularly important when measuring resistances above 100 k Ω . Settling due to RC time constant effects can be quite long. Some precision resistors and multi-function calibrators use large parallel capacitors (1000 pF to 0.1 μ F) with high resistor values to filter out noise currents injected by their internal circuitry. Non-ideal capacitances in cables and other devices may have much longer settling times than expected just by RC time constants, due to dielectric absorption (soak) effects. Errors will be measured when settling after the initial connection and after a range change.

High-resistance measurement errors

When you measure large resistances, significant errors can occur due to insulation resistance and surface cleanliness. You should take the necessary precautions to maintain a “clean” high-resistance system. Test leads and fixtures are susceptible to leakage due to moisture absorption in insulating materials and “dirty” surface films. Nylon and PVC are relatively poor insulators (109 Ω) compared to PTFE insulators (1013 Ω). Leakage from nylon or PVC insulators can easily contribute a 0.1% error when measuring a 1 M Ω resistance in humid conditions.

DC Current Measurement Errors

When you connect the multimeter in series with a test circuit to measure current, a measurement error is introduced, caused by the multimeter's series burden voltage. A voltage is developed across the wiring resistance and current shunt resistance of the multimeter, as shown in Figure 2.




Figure 2

AC Current Measurement Errors

Burden voltage errors, which apply to DC current, also apply to AC current measurements. However, the burden voltage for AC current is larger due to the multimeter's series inductance and the measurement connections.

The burden voltage increases as the input frequency increases. Some circuits may oscillate when performing current measurements due to the multimeter's series inductance and the specific measurement connections.

Frequency and Period Measurement Errors

The Keysight 34461A uses a reciprocal counting technique to measure frequency and period to generate constant measurement resolution for any input frequency. The 34461A's AC voltage measurement section performs input signal conditioning. All frequency counters are susceptible to errors when measuring low-voltage, low-frequency signals. The effects of both internal noise and external noise pickup are critical when measuring "slow" signals. The error is inversely proportional to frequency. Measurement errors will also occur when you attempt to measure the frequency (or period) of an input following a DC offset voltage change. To avoid this, allow the multimeter's input DC blocking capacitor to fully settle before making frequency measurements.

Conclusion

When measuring small resistance or low current, it is important to take extra precautions to make quality measurements. Once the system settling times have been determined, the reading delay times can be set to optimize measurement time and increase system throughput.

For more information about the Keysight 34461A DMM, go to www.keysight.com/find/34461A

Evolving

Our unique combination of hardware, software, support, and people can help you reach your next breakthrough. **We are unlocking the future of technology.**



From Hewlett-Packard to Agilent to Keysight

For more information on Keysight Technologies' products, applications or services, please contact your local Keysight office. The complete list is available at: www.keysight.com/find/contactus

Americas

Canada	(877) 894 4414
Brazil	55 11 3351 7010
Mexico	001 800 254 2440
United States	(800) 829 4444

Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 11 2626
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Other AP Countries	(65) 6375 8100

Europe & Middle East

Austria	0800 001122
Belgium	0800 58580
Finland	0800 523252
France	0805 980333
Germany	0800 6270999
Ireland	1800 832700
Israel	1 809 343051
Italy	800 599100
Luxembourg	+32 800 58580
Netherlands	0800 0233200
Russia	8800 5009286
Spain	800 000154
Sweden	0200 882255
Switzerland	0800 805353
	Opt. 1 (DE)
	Opt. 2 (FR)
	Opt. 3 (IT)
United Kingdom	0800 0260637

For other unlisted countries:
www.keysight.com/find/contactus
 (BP-2-23-17)



www.keysight.com/go/quality
 Keysight Technologies, Inc.
 DEKRA Certified ISO 9001:2015
 Quality Management System

This information is subject to change without notice.
 © Keysight Technologies, 2013 - 2017
 Published in USA, March 9, 2017
 5988-5512EN
www.keysight.com

myKeysight

myKeysight
www.keysight.com/find/mykeysight
 A personalized view into the information most relevant to you.

KEYSIGHT SERVICES

Accelerate Technology Adoption.
 Lower costs.

Keysight Services
www.keysight.com/find/service
 Our deep offering in design, test, and measurement services deploys an industry-leading array of people, processes, and tools. The result? We help you implement new technologies and engineer improved processes that lower costs.



www.axistandard.org
 AdvancedTCA® Extensions for Instrumentation and Test (AXIe) is an open standard that extends the AdvancedTCA for general purpose and semiconductor test. Keysight is a founding member of the AXIe consortium. ATCA®, AdvancedTCA®, and the ATCA logo are registered US trademarks of the PCI Industrial Computer Manufacturers Group.



www.lxistandard.org
 LAN eXtensions for Instruments puts the power of Ethernet and the Web inside your test systems. Keysight is a founding member of the LXI consortium.



www.pxisa.org
 PCI eXtensions for Instrumentation (PXI) modular instrumentation delivers a rugged, PC-based high-performance measurement and automation system.



Three-Year Warranty
www.keysight.com/find/ThreeYearWarranty
 Keysight's committed to superior product quality and lower total cost of ownership. Keysight is the only test and measurement company with three-year warranty standard on all instruments, worldwide. And, we provide a one-year warranty on many accessories, calibration devices, systems and custom products.

Keysight Channel Partners
www.keysight.com/find/channelpartners
 Get the best of both worlds: Keysight's measurement expertise and product breadth, combined with channel partner convenience.

www.keysight.com/find/34461A